

ASCII	Dec	Hex
NUL (null)	0	00
SOH (start of heading)	1	01
STX (start of text)	2	02
ETX (end of text)	3	03
EOT (end of transmission)	4	04
ENQ (enquiry)	5	05
ACK (acknowledge)	6	06
BEL (bell)	7	07
BS (backspace)	8	08
HT (horizontal tab)	9	09
LF (line feed)	10	0A
VT (vertical tab)	11	0B
FF (form feed)	12	0C
CR (carriage return)	13	0D
SO (shift out)	14	0E
SI (shift in)	15	0F
DLE (data link escape)	16	10
DC1 (device control 1)	17	11
DC2 (device control 2)	18	12
DC3 (device control 3)	19	13
DC4 (device control 4)	20	14
NAK (negative acknowledge)	21	15

ASCII	Dec	Hex
SYN (synchronous idle)	22	16
ETB (end of transmission block)	23	17
CAN (cancel)	24	18
EM (end of medium)	25	19
SUB (substitute)	26	1A
ESC (escape)	27	1B
FS (file separator)	28	1C
GS (group separator)	29	1D
RS (record separator)	30	1E
US (unit separator)	31	1F
SP (space)	32	20
!	33	21
"	34	22
#	35	23
\$	36	24
%	37	25
&	38	26
'	39	27
(40	28
)	41	29
*	42	2A
+	43	2B

ASCII	Dec	Hex
,	44	2C
-	45	2D
.	46	2E
/	47	2F
A	65	41
0	48	30
1	49	31
2	50	32
3	51	33
4	52	34
5	53	35
6	54	36
7	55	37
8	56	38
9	57	39
:	58	3A
;	59	3B
<	60	3C
=	61	3D
>	62	3E
?	63	3F
@	64	40

ASCII	Dec	Hex
B	66	42
C	67	43
D	68	44
E	69	45
F	70	46
G	71	47
H	72	48
I	73	49
J	74	4A
K	75	4B
L	76	4C
M	77	4D
N	78	4E
O	79	4F
P	80	50
Q	81	51
R	82	52
S	83	53
T	84	54
U	85	55
V	86	56
W	87	57

ASCII	Dec	Hex
X	88	58
Y	89	59
Z	90	5A
[91	5B
\	92	5C
]	93	5D
^	94	5E
_	95	5F
`	96	60
a	97	61
b	98	62
c	99	63
d	100	64
e	101	65
f	102	66
g	103	67
h	104	68
i	105	69

ASCII	Dec	Hex
j	106	6A
k	107	6B
l	108	6C
m	109	6D
n	110	6E
o	111	6F
p	112	70
q	113	71
r	114	72
s	115	73
t	116	74
u	117	75
v	118	76
w	119	77
x	120	78
y	121	79
z	122	7A
{	123	7B
	124	7C
}	125	7D
~	126	7E
DEL	127	7F